

Low voltage

device that disconnects high voltage

Note: Please see our $\underline{\text{emergency response guide}}$ for more information

Cable cut


Airbag

X* X X *X





1. Identification / recognition













3. Disable direct hazards / safety regulations

Deactivation of the high-voltage system

In all other cases, the high-voltage system should be deactivated as follows:

Option 1: High-voltage disconnect








The high-voltage disconnect device is located behind the side panel of the instrument panel on the left (viewed in the direction of travel).

Remove side panel (1) of instrument panel / Disconnect plug (2)

Option 2: Alternative high-voltage disconnect



The alternative high-voltage disconnect device is located behind the footwell trim on the passenger side. It is marked with an information label.





Fold back the footwell trim (1) / Sever the line at the marked point (2) $\,$



In order to ensure that there is no longer any residual voltage in the high-voltage system, wait approx. 20 seconds after switching it off.



The passive safety systems such as airbags and seat belt pretensioners will continue to be supplied with power by the 12-volt electrical system.



Disconnecting the 12 V battery

